

Wireless Laser Barcode Scanner

- MS836B -



User Manual

Version 2.6

Change Log

Date	Change Description	Version
2021/10/29	first published version	1.0
2021/11/02	Update Ch.2 ,Ch.3 and Appendix	1.1
2021/11/10	Update Ch.3 and Appendix	1.2
2021/12/02	Remove 3.23 Prefix Sequence	1.3
2021/12/13	Update Ch.2 ,Ch.3 and Appendix	1.4
2022/1/7	Update Ch.2 ,Ch.3 and Appendix	1.5
2022/4/26	Update 1.3 Specification	1.6
2022/5/24	Add Appendix E	1.7
2022/6/06	Update USB Interface	1.8
2022/07/25	Change micro USB to USB Type-C	1.9
2023/05/12	Update 2.9 Auto Power Off After Idle: Change default from 1 min to 5 min	2.0
2023/5/29	Add note to 2.8 Auto Power Off After Idle	2.1
2023/10/17	Add GS1 AI setting	2.2
2023/10/02	Update Specification Descriptions	2.3
2023/11/20	Add Engine Factory Default Barcode Add Power-Up Beep Sound On/Off Setting	2.4
2024/8/15	Update IP Rating (IP42 > IP52)	2.5
2025/4/8	Update IP Rating	2.6

Preface

About This Manual

Thank you for purchasing the Unitech product.
This manual explains how to install, operate and maintain our product.
No part of this publication may be reproduced or used in any form, or by any electrical or mechanical means, such as photocopying, recording, or information storage and retrieval systems, without permission in writing from the manufacturer. The material in this manual is subject to change without notice. All product and company names are trademarks, service marks, or registered trademarks of their respective owners.

Regulatory Compliance Statements



FCC Warning Statement

This device has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference with radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference with radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and receiver.
 - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
1. This transmitter must not be co-located or operating in conjunction with

- any other antenna or transmitter.
2. This device complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. To maintain compliance with FCC RF exposure requirements, avoid direct contact to the transmitting antenna during transmitting.
 3. Any changes or modifications (including the antennas) made to this device that are not expressly approved by the manufacturer may void the user's authority to operate the equipment.

Operation on the 5.15 - 5.25GHz frequency band is restricted to indoor use only. The FCC requires indoor use for the 5.15-5.25GHz band to reduce the potential for harmful interference to co-channel Mobile Satellite Systems. Therefore, it will only transmit on the 5.25-5.35 GHz, 5.47-5.725 GHz and 5.725 - 5.850 GHz band when associated with an access point (AP).

FCC Label Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference.
2. This device must accept any interference received, including interference that may cause undesired operation.

RF Radiation Exposure Statement

For body contact during operation, this device has been tested and meets FCC RF exposure guidelines when used with an accessory that contains no metal and that positions the handset a minimum of 1.5 cm from the body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines.

Canadian Compliance Statement

This Class B Digital apparatus meets all requirements of the Canadian Interference-Causing Equipment Regulations.

Cet appareil numérique de la classe B respecte les exigences du Règlement sur le matériel brouilleur du Canada.

European Conformity Statement

Unitech Electronics co., Ltd herewith declares that the Unitech product is in compliance with the essential requirements and all other provisions of the RED 2014/53/EU directive, the EMC 2014/30/EU directive and the Low Voltage 2014/35/EU directive.

The declaration of conformity is available for download at :

<https://portal.Unitech.eu/public/Safetyregulatorystatement>

CE RF Exposure Compliance

This device meets EU requirements (2014/53/EU) on the limitation of exposure of the general public to electromagnetic fields by way of health protection.

For body-worn operation, this device has been tested and meets the ICNIRP guidelines and the European Standard EN 62209-2, for use with dedicated accessories, SAR is measured with this device at a separation of 0.5 cm to the body, while transmitting at the highest certified output power level in all frequency bands of this device. Use of other accessories which contain metals may not ensure compliance with ICNIRP exposure guidelines.

CE Mark Warning




This equipment complies with the requirements of Directive 2014/53/EU of the European Parliament and Commission from 24 May, 2014 governing Radio and Telecommunications Equipment and mutual recognition of conformity.

RoHS Statement



This device conforms to RoHS (Restriction of Hazardous Substances) European Union regulations that set maximum concentration limits on hazardous materials used in electrical and electronic equipment.

Waste electrical and electronic equipment (WEEE)



Unitech has set up a policy and process to meet the EU directive 2002/96/EC and update 2003/108/EC concerning electronic waste disposal.

For more detailed information of the electronic waste disposal of the products you have purchased from Unitech directly or via Unitech's resellers, you shall either contact your local supplier or visit us at :

<https://portal.Unitech.eu/public/WEEE>

Taiwan NCC Warning Statement

NCC 警語

取得審驗證明之低功率射頻器材，非經核准，公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。

低功率射頻器材之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。

前述合法通信，指依電信管理法規定作業之無線電通信。低功率射頻器材須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

注意事項：

1. 使用過度恐傷害視力。
2. 使用30分鐘請休息10分鐘；2歲以下幼兒不看螢幕，2歲以上每天看螢幕不要超過1小時。
3. 減少電磁波影響，請妥適使用。

Laser Information

The Unitech product is certified in the U.S. to conform to the requirements of DHHS/CDRH 21CFR Subchapter J and to the requirements of IEC 825-1. Class II and Class 2 products are not considered to be hazardous. The Unitech product contains internally a Visible Laser Diode (VLD) whose emissions do not exceed the maximum limits as set forth in the above regulations. The scanner is designed so that there is no human access to harmful laser light during normal operation, user maintenance or prescribed service operations.

The laser safety warning label required by the DHHS/IEC for the Unitech product's optional laser scanner module is located on the memory compartment cover, on the back of the unit.

* Laser information only applies to the products with laser components.

CAUTION! Use of controls or adjustments or performance of procedures other than those specified herein may result in hazardous laser light. Use of optical instruments with the scanner, including binoculars, microscopes, and magnifying glasses, with will increase eye damage. This does not include eyeglasses worn by the user.

LED Information

The Unitech product contains LED indicator(s) or LED ring whose luminance is not harmful to human eyes during normal operation, user maintenance or prescribed service operations.

*LED information only applies to the products with LED components.

Battery Notice

1. To guarantee optimal performance, it is recommended that rechargeable batteries be replaced every year, or after 500 charging cycles are completed. It is normal for the battery to balloon or expand after one year or 500 cycles. Although it does not cause damage, it cannot be used again and must be disposed of according to the location's safe battery disposal procedures.
2. If a battery performance decreases more than 20%, the battery is at the end of its life cycle. Stop use and ensure the battery is disposed of properly.
3. The length of time that a battery lasts depends on the battery type and how the device is used. Conserve the battery life by doing the following:
 - Avoid fully uncharging the battery because this places additional strain on it. Several partial uncharges with frequent charges are better than a fully uncharged battery. Charging a partially charged battery does not cause harm to the unit.
 - Keep the battery cool. Avoid hot vehicles. For prolonged storage, keep the battery at a 40% charge level.
 - Do not leave the battery uncharged and unused for an extended period of time, the battery will wear out and the longevity of the battery will be at least half of one with frequent charges.
4. Protect battery life by not over or under charging the battery.
5. Please do not leave battery unused for long time without charging it. Despite Unitech's safety precautions, the battery pack may begin to change shape. If so, stop using it immediately. Please check to see if you are using a proper power adapter to charge the battery or contact your service provider for service.
6. If you cannot charge the battery after it has been idle for an extended period of time and it begins to heat up, please do not try to charge it. It may not be functional anymore.
7. Please only use the original battery from Unitech. Using a third party battery can damage our products. Please note that when such damage occurs, it is not covered by your warranty.

CAUTION!

- RISK OF EXPLOSION IF BATTERY IS REPLACED INCORRECTLY.
DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS.
- 如果更換不正確之電池行事會有爆炸的風險
請依製造商說明書處理用過之電池
- 如果更換不正確之電池行事會有爆炸的風險
請依製造商說明書處理用過之電池

Battery charge notice

It is important to consider temperature when the battery pack is charging. Charging is most efficient at normal room temperature or in a slightly cooler environment. It is essential that batteries are charged within the stated range of 0°C to 40°C. Charging batteries outside of the specified range could damage the batteries and shorten their life cycle.

CAUTION! Do not charge batteries at a temperature lower than 0°C. This will make the batteries unstable and dangerous. Please use a battery temperature detecting device for a charger to ensure a safe charging temperature range.

CAUTION! To ensure the unit working properly, please keep all connectors away from the contaminants staying inside of them such as dust, grease, mud, and water. The negligence may cause the unit with no communication, short circuited, overheated and so on.

CAUTION! If the connector is damaged, please ensure the connector is being fully repaired before use the unit to avoid causing short circuited.

Storage and safety notice

Although charged batteries may be left unused for several months, their capacity may be depleted due to build up of internal resistance. If this happens, they will require recharging prior to use. Batteries may be stored at temperatures between -20°C to 60°C, however they may deplete more rapidly at higher temperatures. It is recommended to store batteries at room temperature.

** The message above only applies to the usage of the removable batteries.
For the products with non-removable batteries / without batteries, please refer to the specification of each product.*

Product Operation and Storage Notice

The Unitech product has applicable operation and storage temperature conditions. Please follow the limitation of suggested temperature conditions to avoid failure, damage or malfunction.

**For applicable temperature conditions, please refer to the specification of each product.*

Adapter Notice

1. Please do not leave the power adapter in the socket when it is not connected to your Unitech product for charging.
2. Please remove the power adapter when the battery is fully recharged.
3. The bundled power adapter that comes with your Unitech product is not meant to be used outdoors. An adapter exposed to water or rain, or a very humid environment can cause damage to both the adapter and the product.
4. Please only use the bundled power adapter or same specification of adapter to charge your Unitech product. Using the wrong power adapter can damage your Unitech product.

** The message above only applies to the product connected to the adapter.
For the products without using the adapters, please refer to the specification of each product.*

Hearing Damage Warning

To prevent possible hearing damage, do not listen at high volume levels for long periods.



Figure 1 – Warning label (IEC 60417-6044)

Worldwide Support

Unitech's professional support team is available to quickly answer questions or assist with technical-related issues. Should an equipment problem occur, please contact the nearest Unitech regional service representative.

For complete contact information please visit the Web sites listed below:

Taipei, Taiwan – Headquarters Tel: +886-2-89121122 E-mail: info@hq.ute.com Address: 5F, No. 136, Lane 235, Baoqiao Road, Xindian District, New Taipei City 231, Taiwan (R.O.C.) Website: http://www.ute.com	Europe Tel: +31-13-4609292 E-mail: info@eu.ute.com Address: Kapitein Hatterasstraat 19, 5015 BB, Tilburg, the Netherlands Website: http://eu.ute.com
China Tel: +86-59-2310-9966 E-mail: info@cn.ute.com Address: Room401C, 4F, RIHUA International Mansion, Xinfeng 3rd Road, Huoju Hi-tech District, Xiamen, Fujian, China Website: http://cn.ute.com	Japan Tel: +81-3-62310896 E-mail: info@jp.ute.com Address: Tosei Building 3F.,18-10 Nihonbashi-Hakozakicho, Cyuouku, Tokyo, 103-0015, Japan Website: http://jp.ute.com
Asia & Pacific / Middle East Tel: +886-2-27911556 E-mail: info@apac.ute.com info@india.ute.com info@mideast.ute.com Address: 4F., No. 236, ShinHu 2nd Rd., NeiHu Chiu, 114, Taipei, Taiwan Website: http://apac.ute.com / http://mideast.ute.com	Latin America Tel: +52-55-5171-0528 E-mail: info@latin.ute.com Address: 17171 Park Row, Suite 210 Houston, TX 77084USA (Rep.) Website: http://latin.ute.com
North America Tel: +1-714-8916400 E-mail: info@us.ute.com / info@can.ute.com Address: 6182 Katella Ave, Cypress, CA 90630, USA Website: http://us.ute.com	Please scan QRCode to visit us: 

Warranty Policy

The items covered under the Unitech Limited Warranty are free from defects during normal use.

The warranty period is varied from each country. Please consult with your supplier or Unitech local office for actual length of warranty period to your purchased product.

Warranty becomes void if equipment is modified, improperly installed or used, damaged by accident or neglect, or if any parts are improperly installed or replaced by the user.

Table of Contents

Preface.....	i
About This Manual	i
Regulatory Compliance Statements	i
Laser Information	vi
LED Information	vi
Battery Notice.....	vii
Adapter Notice.....	x
Hearing Damage Warning	x
Worldwide Support	xi
Warranty Policy	xii
Chapter 1 - Overview.....	1
1.1 Package	1
1.2 Product Detail	2
1.3 Specifications	3
1.4 Getting Started	5
1.5 Battery Charging	7
1.6 LED / Beeper Indicator	8
Chapter 2 – Command Setting.....	9
2.1 Barcode Programming	9
2.2 Scanner Type	10
2.3 Output Method.....	11
2.4 System Reset	11
2.5 Operation Mode.....	12
2.6 Wireless 2.4G Setting.....	13
2.7 Bluetooth	15
2.8 Data Terminator	19
2.9 Auto Power Off After Idle	20
2.10 Beeper Control	21
2.11 Good Read Indicator.....	22
2.12 Sound Frequency Setting	22

2.13 Battery Display	22
2.14 HID Keyboard Case	22
2.15 HID Keyboard Language	23
2.16 GS Characters Conversion.....	25
2.17 Reading Length Setting for all Codes	27
2.18 Beep Tones	28
Chapter 3 – Symbology	30
3.1 Return to Factory Default for all Symbology	30
	30
3.2 Codabar.....	31
3.3 Code 39.....	34
3.4 Code 32.....	37
3.5 Interleaved 2 of 5.....	39
3.6 Industrial 2 of 5.....	41
3.7 Matrix 2 of 5.....	43
3.8 Chinese Postal 2 of 5	45
3.9 Standard 2 of 5	47
3.10 MSI	49
3.11 Code 93	52
3.12 Code 11	54
3.13 Code 128.....	57
3.14 GS1 Databar	60
3.15 UPC-A	65
3.16 UPC-E	67
3.17 EAN/JAN-8.....	69
3.18 EAN/JAN-13	71
3.19 ISBN	75
3.20 ISSN	75
3.21 Supplements +2/+5	76
3.22 UK/Plessey.....	77
3.23 Code ID	79
3.24 Febraban Transfer Function	79
Appendix A – Digit Barcodes	80
A.1 ASCII Code Table (for Software Decoder Version)	80

A.2 Default Barcode Parameter Setting Table	88
A.3 Default Setting Table	89
Appendix B – Hidden Character	90
B-1 Hide The Previous Character Shortcut Settings	90
B-2 Shortcut Settings to Hidden back character	92
Appendix C – ASCII Code Table (for RFID Module)	94
Appendix D – Function Code for Serial Port and USB Virtual Serial Port	104
Appendix E – The Default Value	106
Of Each Symbology's Length	106
Within Range	106

Chapter 1 - Overview

1.1 Package

Please make sure the following contents are in the MS836B gift box.
If something is missing or damaged, please contact your Unitech representative.

The package contents (without cradle):

- MS836B Scanner with Battery
- USB Type-C Charging Cable
- 2.4G Receiver
- Quick Start Guide
- Regulatory Compliance Statements

Note: Please charge with USB Type-C Charging cable.

NOTE: *The barcode with an asterisk (*) which appears in the following chapters indicates that it is the default option for the corresponding setting.*

1.2 Product Detail

■ Scanner details



1.3 Specifications

Optical & Performance	
Sensor	1D Laser Engine
Aiming Element	Laser
Ambient Light	0-100,000 Lux
Scan Rate	100 times/ sec
Skew Angle	±60°
Memory	16MB
Optical Resolution	4mil (code 39)
Depth of Field	10mm-265mm(13 mil, EAN13, PCS=90%)
Communication	
Radio	2.4G Wireless
Wireless Coverage	2.4G: 100M (line of sight)
Bluetooth	V4.2 Class II
Bluetooth Coverage	10M
Interface/ Profile	2.4G: USB Bluetooth: HID, BLE ,SPP
Host Interface supported	USB Type-C
Mechanical	
Dimension	174mm × 72mm × 96mm (L x W x H)
Weight	216g
Functionality	
Operation Mode	Trigger Mode, Buffer Mode

Regulatory Approvals	
CE, FCC, BSMI, VCCI	
Symbologies	
1D	Industial 2 of 5, Standard 25, Matrix 25, China post 25, Code 11, Codabar, MSI/plessey, UK/plessey, Code39 (Standard 39& Full ASCII Code 39) Code 32, Code 93, Code128, UPC-A, UPC-E, EAN 13, EAN 8, UPC/EAN add-on 2/5, ISBN, ISSN, GS1(RSS) RSS-14, LIMITED, EXPENDED, Include GS1 STACK
Data Formatting	Prefix, Suffix, Code ID
Electrical	
Operation Voltage	DC 5V
Current Consumption	Operation mode: < 135 mA Standby mode: < 85mA
Indicator	Buzzer LED light
Battery Type	Lithium-ion
Battery Capacity	2600mAh 18650 battery
Battery Charging time	Fully charged in 5 hours
Operating Time	Over 30 hours (continuous working)
Environmental	
Mechanical Shock	1.5m onto concrete (scanner only)
Operating Temperature	-10°C to 50°C
Storage Temperature	-20°C to 60°C
Relative Humidity	5% to 90% non-condensing
IP Rating	IP42
Package Contents	
<ul style="list-style-type: none"> • MS836B scanner • 2.4G Receiver • USB Type-C Charging Cable 	

1.4 Getting Started

1.4.1 How to pair the scanner with the receiver

Connect the USB receiver to the host. Plug the USB Receiver to a free USB port of a host computer. The MS836B is now ready to use.



■ LED Description

Green Light	Slow flash	Scanner is not connected to receiver or USB.
	Flash	Scanner is connected to receiver or USB.
	Quick flash	Entering the pairing mode.
	Flash once	Flash once : Scanned data being uploaded successfully.

Scanner Turn on: Long press the trigger key for 2 seconds until you hear a long beep sound.


1.4.2 Test & Finish

Open a word processing program such as Microsoft Word or Notepad and scan the following barcode:




If the word “Unitech” appears on the screen, you have successfully installed your scanner.

Note: To scan a barcode, make sure the aiming beam crosses every bar and space of the barcode.



1.5 Battery Charging

Before you use the MS836B for the first time, we strongly recommend charging the battery. It takes approximately 5 hours to fully charge the battery. To charge the scanner without a cradle, please follow the instructions below. Please only use the USB Type-C cable which came with the package.




■ Charging through USB Type-C cable

To charge MS836B, please connect scanner with host PC through USB Type-C cable.

1.6 LED / Beeper Indicator

Division	Red LED Light	Green LED Light	BEEP / Sound
Battery charging	Red light always on		
Battery Fully charged	Red light out		
Power On			One Long Beep
2.4 G Receiver Pairing		Green light keeps flashing	
Bluetooth Pairing		Green light keeps flashing	
Bluetooth SPP/BLE Pairing		Slow Flash	
USB connection success		Green light always on	One short Beep
2.4 G Receiver connection success		Green light always on	One short Beep
Bluetooth connection success		Green light always on	One short Beep
Barcode Good Read		Green light flash once	One short Beep
Wireless Setting Sound			Two High Beeps
Bluetooth Transmission Failed			Three short Beeps
Mode Setting success			High and Low Beeps
Data saved success			High and Low Beeps
Data upload complete			High and Low Beeps
Auto Power Off			High and Low Beeps
USB disconnection			Three short Beeps
2.4 G Receiver disconnection			Three short Beeps
Bluetooth disconnection			Three short Beeps
Data upload failed			Three short Beeps
Flash memory is full			Three short Beeps
Auto Power Off under Low Battery			Three short Beeps and High and Low Beeps



Chapter 2 – Command Setting

2.1 Barcode Programming


Use of Programming Barcodes

Before starting scanning any setting barcode, please do follow the instruction below. Scanning the Enter Setup barcode can enable the engine to enter the setup mode. Then you can scan a number of programming barcodes to configure your engine. To exit the setup mode, scan the Exit Setup barcode.


Enter Setup




Exit Setup



Exit Setup





2.2 Scanner Type

2.2.1 Wireless Communication Mode

2.4 G Receiver Mode *



Note: For more information, please refer to [• 2.6 Wireless 2.4G Setting.](#)

Bluetooth HID Mode



Note: For more information, please refer to [• 2.7.1Bluetooth HID Mode](#)

Bluetooth BLE Mode




Bluetooth SPP Mode




Note:

- *To switch the different scanner type, please do un-pair first and then select the scanner type and redo Bluetooth connection.*

Exit Setup





2.2.2 USB Interface Mode

USB-HID *



USB-COM



2.3 Output Method

USB Priority Output*



Simultaneous Output
(USB,2.4G& Bluetooth)



2.4 System Reset

RF Module Factory Default



Engine Factory Default




Software Decoder Version



Wireless Version



Exit Setup





2.5 Operation Mode

Wedge Mode



Batch Mode



Auto Mode *



2.5.1 Batch Mode

Upload all data



Note: Scan the "Upload all data" code to complete the data transfer.

Clear all data




Note: Clear all data mode is only effective under Batch mode.

Display stored data



Exit Setup





2.6 Wireless 2.4G Setting

2.4G Receiver Mode *



Scan the “2.4G Receiver Mode” barcode to enter the 2.4G receiver mode automatically and connect to the receiver which is matched last time by default.

One scanner pairing to one receiver is the factory default. If you want to pair with a new receiver, please refer to the following instructions.

Pairing with new receiver

There are two ways to pair with the new receiver:

- A. Scan the “2.4G Receiver Pairing” barcode.
- B. Long press the button for about 16 seconds.

A. Scan the “2.4G Receiver Pairing” barcode

- (1) Remove the original receiver.
- (2) Scan the following barcode:

2.4G Receiver Pairing





- (3) Insert the receiver you want to connect with into your device. You will hear a short beep when pairing succeeds.

B. Long press the button for about 16 seconds

- (1) Remove the original receiver.
- (2) Long press the button for about 16 seconds. During the process, there will be 2 sounds respectively; first sound at the 8th second, the second at the 16th second, then release the button.

Exit Setup






Long press 16 seconds to Enter 2.4G pairing Mode

Enable



Disable *





Exit 2.4G Pairing:

- (1) When the Receiver is matched, it will prompt once and ending pairing.
- (2) Double-click the button to exit and it will prompt once.
- (3) If the receiver is not connected within 1 minute, it will exit automatically and with 3 beeps.

Note: When exiting the pairing, if the receiver is not connected, it will connect to the receiver which is matched last time automatically by default.

Exit Setup





2.7 Bluetooth

2.7.1 Bluetooth HID Mode

Bluetooth HID Mode



Note: Scan this barcode to enter the “Bluetooth HID Mode” and it will connect to the Bluetooth® which is matched last time automatically by default.

2.7.2 Bluetooth HID Pairing

Bluetooth HID Pairing



1. Enter “Bluetooth HID Pairing” mode:

Scan this barcode to enter the “Bluetooth HID Pairing” mode, or long press 8 seconds until you hear a short beep, then release the button.

2. Exit “Bluetooth HID Pairing” mode:

- (1) Double-click the button, and you will exit the “Bluetooth HID Pairing” mode after one short beep.
- (2) If the Bluetooth is not matched within 1 minute, it will exit automatically and with three short beeps.

Enable/Disable “Bluetooth HID Pairing” mode:


Enable




Disable *



Exit Setup





2.7.3 Show & Hide the HID Virtual Keyboard in IOS

Show & Hide the HID Virtual Keyboard in IOS



Note: Quick press three times to enable show or hide IOS virtual keyboard function.

2.7.4 Bluetooth HID Transfer Rate Setting

Fast



Medium *



Low




Ultra-low




Note:

1. Fast speed uploading is recommended in IOS.
2. Set the corresponding speed according to the response speed of the phone under Android system.
3. When the uploaded data is messed up and lost, try to turn down the speed.

Exit Setup





2.7.5 Bluetooth BLE/SPP Mode

Bluetooth BLE Mode



Bluetooth SPP Mode



2.7.6 Bluetooth Name Setting

Bluetooth Name Setting



^&C0C&^MS836B

The front character “^&C0C&^” is fixed and ‘MS836B’ is the name that needs to be set.

(For example, if you want to set the scanner name as “123”, you will need to create a barcode named “^&C0C&^123”.)

Note:

1. The Bluetooth® name can only be set within 24 bytes.
2. The name of Bluetooth HID/SPP/BLE all changed after modifying.


Bluetooth Name ASCII Setting




Steps:

1. Scan "Bluetooth Name ASCII Setting" barcode.
2. Please refer to the [Appendix C-ASCII code table \(for RFID module\)](#), and scan the contents that needs to be added in sequence.
3. Scan "Save and Finish Setting" barcode below.

Exit Setup



**Save and Finish Setting**

Note: The Bluetooth® name can only be set within 24 bytes.

Bluetooth Name Default**Note:**


Scan the “Bluetooth Name Default” barcode Or the “[Factory Default](#)” barcode to clear the customized Bluetooth® names.


2.7.7 Get Bluetooth Name

Get Bluetooth Name

Note: This code only worked under the Bluetooth HID/SPP/BLE mode.

2.7.8 Encoding

Keyboard Function Key ***Send ASCII****Exit Setup**



2.8 Data Terminator

CR *



CR/LF



LF




None




TAB



Exit Setup





2.9 Auto Power Off After Idle

Disable



Immediate Sleep



10s



30s



1min



2min



5min *




10min



30min




Exit Setup



***Note:**

The Auto Power Off After Idle may have a $\pm 5s$ gap. The calculation method for Auto Power Off is from the release of the button to the shutdown of the scanner.



2.10 Beeper Control

Off



Note: The Off Code only turns off the short high beep of data send, the setting sound still exists

High *



Medium



Low



2.10.1 Power-Up Beep Sound

Beep Sound ON*



Beep Sound OFF




Engine Beep Sound ON*




Engine Beep Sound OFF



Exit Setup





2.11 Good Read Indicator

Default Beeps *



One Beep



2.12 Sound Frequency Setting

2048 Hz



2700 Hz




2.13 Battery Display

Display Battery Capacity



Exit Setup



2.14 HID Keyboard Case



Normal Letter Case *



All Upper Case



All Lower Case



Case Inversion



2.15 HID Keyboard Language

USA *



German



France




Italy




Canadian



Exit Setup





Spain



Brazil



Sweden



Portugal



Belgium



Turkey-F



Turkey-Q



Italian14



Netherlands




Poland



Finland



Exit Setup





Latin America



Serbia



Hungary



Denmark



Norway



Japan



2.16 GS Characters Conversion

None *




GS Converts To <GS>




GS Converts To |



Exit Setup






GS converts to]




GS Converts To ^]




Exit Setup






2.17 Reading Length Setting for all Codes

Minimum length for all Codes



Maximum length for all Codes




Note: Reading length setting for all codes is used to limit the barcode length that can be read (is subjected to the data length).


Example:

Set the reading length as 5-10 digit.

Scan "Enter" "Minimum length for all Codes" "0" "0" "5" "Maximum length for all Codes" "0" "1" "0" "Exit". After that, any barcodes shorter than 5 digits or longer than "10" digits cannot be read successfully.


Exit Setup





2.18 Beep Tones


None



Beep Duration Short




Beep Duration Medium *



Beep Duration Long



Set as Customized Duration



Customized Duration (0.01-2.55s)




Example:

If scanner needs 200ms of customized duration, duration time $T = N \times 10$,
 $200 \text{ ms} = N \times 10$, $N = 20$.


So scan: "Enter" "Customize duration" "0" "2" "0" "Set as customized duration"
 "Exit".

Exit Setup






Low



Medium *




High



Set as Customized Tone



Customized Tone (100-2550Hz)



Example:

If scanner needs 200Hz of customized tone, customized tone = $N \times 10$,

200Hz = $N \times 10$, $N = 20$.

So scan: "Enter" "Customize tone" "0" "2" "0" "Set as customized tone" "Exit".


Starting Sound On *



Starting Sound Off



Exit Setup





Chapter 3 – Symbology

3.1 Return to Factory Default for all Symbologies


Return to Factory Default



Note: In the following chapters, please refer to [A.1-ASCII Code Table \(for Software Decoder Version\)](#) when Setting Length Range and Setting Prefix/Suffix for Symbologies.

Note: For the default values of each symbology's length within range, please refer to [Appendix E](#).

Exit Setup





3.2 Codabar

Enable *




Disable



3.2.1 Check Digit Verification


Enable



Disable *




Transmit Check Digit After
Verification




Do Not Transmit Check Digit
After Verification *



Exit Setup






3.2.2 Transmit Start/Stop Character

Transmit Start/Stop Character



Do Not Transmit Start/Stop
Character *



Transmit Start/Stop ABCD/ABCD




Transmit Start/Stop ABCD/TN*E




Exit Setup






3.2.3 Set Length Range for Codabar

Minimum Length



Maximum Length




3.2.4 Prefix/Suffix for Codabar


Codabar Prefix



Codabar Suffix




Exit Setup






3.3 Code 39

Enable *




Disable




3.3.1 Code 39 Check Digit Verification


Enable



Disable *




Do Not Transmit Check Digit
After Verification *




Transmit Check Digit After
Verification




Exit Setup






3.3.2 Transmit Start/Stop Character

Transmit Start/Stop Character




Do Not Transmit Start/Stop Character *




3.3.3 Code 39 Full ASCII


Full ASCII 39 *




3.3.4 Standard 39



Exit Setup





3.3.5 Set Length Range for Code 39

Minimum Length




Maximum Length



3.3.6 Prefix/Suffix for Code 39


Code 39 Prefix



Code 39 Suffix



Exit Setup






3.4 Code 32

3.4.1 Code 32

Enable



Disable *



3.4.2 Transmit Code 32 Prefix A


Transmit Code 32 Prefix A



Do Not Transmit Code 32 Prefix A *




Exit Setup





3.4.3 Transmit Code 32 Check Digit

Transmit Code 32 Check Digit



Do Not Transmit Code 32

Check Digit *



3.4.4 Prefix/Suffix for Code 32


Code 32 Prefix




Code 32 Suffix




Exit Setup






3.5 Interleaved 2 of 5

Enable *




Disable




3.5.1 Interleaved 2 of 5 Check Digit Verification


Enable




Disable *



Transmit Check Digit



Do Not Transmit Check Digit *




Exit Setup





Transmit the first 0 *




Do Not Transmit the first 0




3.5.2 Set Length Range for Interleaved 2 of 5

Minimum Length



Maximum Length




3.5.3 Prefix/Suffix for Interleaved 2 of 5


Interleaved 2 of 5 Prefix



Interleaved 2 of 5 Suffix




Exit Setup






3.6 Industrial 2 of 5

Enable




Disable*




3.6.1 Check Digit Verification


Enable




Disable *




Transmit Check Digit After Verification




Do Not Transmit Check Digit After
Verification *



Exit Setup






3.6.2 Set Length Range for Industrial 2 of 5

Minimum Length



Maximum Length




3.6.3 Prefix/Suffix for Industrial 2 of 5


Industrial 2 of 5 Prefix



Industrial 2 of 5 Suffix




Exit Setup






3.7 Matrix 2 of 5

Enable




Disable *




3.7.1 Check Digit Verification


Enable



Disable *




Transmit Check Digit After Verification



Do Not Transmit Check Digit
After Verification *



Exit Setup






3.7.2 Set Length Range for Matrix 2 of 5

Minimum Length




Maximum Length




3.7.3 Prefix/Suffix for Matrix 2 of 5


Matrix 2 of 5 Prefix



Matrix 2 of 5 Suffix




Exit Setup





3.8 Chinese Postal 2 of 5

Enable




Disable *



3.8.1 Check Digit Verification


Enable



Disable *




Transmit Check Digit After
Verification



Do Not Transmit Check Digit
After Verification *



Exit Setup






3.8.2 Set Length Range for Chinese Postal

2 of 5

Minimum Length



Maximum Length



3.8.3 Prefix/Suffix For Chinese Postal 2 of 5


Chinese Postal 2 of 5 Prefix




Chinese Postal 2 of 5 Suffix



Exit Setup





3.9 Standard 2 of 5

Enable



Disable *



3.9.1 Check Digit Verification

Enable




Disable *




Transmit Check Digit After Verification




Do Not Transmit Check Digit After
Verification *




Exit Setup





3.9.2 Set Length Range for Standard 2 of 5

Minimum Length




Maximum Length




3.9.3 Prefix/Suffix for Standard 2 of 5


Standard 2 of 5 Prefix




Standard 2 of 5 Suffix




Exit Setup






3.10 MSI

Enable




Disable *




3.10.1 Check Digit Verification


Enable




Disable *




Transmit Check Digit After Verification










Do Not Transmit Check Digit After
Verification *



Exit Setup




**Verify Second Check Digit *****Do Not Verify Second Check Digit****Verification *****Verify First Check Digit, MOD11****Verify First Check Digit, MOD10 *****Verify Second Check Digit, MOD11****Verify Second Check Digit, MOD10 *****Exit Setup**



3.10.2 Set Length Range for MSI

Minimum Length




Maximum Length



3.10.3 Prefix/Suffix for MSI


MSI Prefix



MSI Suffix



Exit Setup





3.11 Code 93

Enable *




Disable




3.11.1 Check Digit Verification


Enable




Disable*



Exit Setup





3.11.2 Set Length Range for Code 93

Minimum Length




Maximum Length



3.11.3 Prefix/Suffix for Code 93


Code 93 Prefix



Code 93 Suffix




Exit Setup






3.12 Code 11

Enable




Disable *



3.12.1 Check Digit Verification


Verify First Check Digit



Do Not Verify First Check Digit*




Transmit Check Digit After Verification



Do Not Transmit Check Digit
After Verification *




Exit Setup






Verify Second Check Digit *



Do Not Verify Second Check Digit



Verify First Check Digit, MOD09



Verify First Check Digit, MOD10 *




Verify Second Check Digit, MOD09



Verify Second Check Digit, MOD10 *




Exit Setup





3.12.2 Set Length Range for Code 11

Minimum Length




Maximum Length




3.12.3 Prefix/Suffix for Code 11


Code 11 Prefix




Code 11 Suffix




Exit Setup






3.13 Code 128

Enable *




Disable




3.13.1 UCC 128

Enable




Disable *



3.13.2 Transmit Check Digit


Transmit Check Digit



Do Not Transmit Check Digit *




Exit Setup






3.13.3 Set Length Range for Code 128

Minimum Length




Maximum Length



3.13.4 Prefix/Suffix for Code 128


Code 128 Prefix




Code 128 Suffix




Exit Setup





3.13.5 GS1-128 AI

No*



Apply




Apply with Separator



Note: Please remind that you should open the UCC-128 setting while using GSI-128 AI.


Exit Setup






3.14 GS1 Databar

GS1 Databar Enable All *




GS1 Databar Disable All




Note: If you scan the GS1 Databar disable all, you have to scan the GS1 Databar Enable all before scanning the following barcodes.

3.14.1 GS1 DataBar-14


Enable *




Disable



Exit Setup






3.14.2 Transmit GS1 DataBar-14 Check Digit

Transmit GS1 Databar

Check Digit *



Do Not Transmit GS1 DataBar Check
Digit



3.14.3 Prefix/Suffix for GS1 Databar-14

GS1 Databar-14 Prefix



GS1 Databar-14 Suffix




3.14.4 AI_GS1 Databar-14


Enable *



Disable




Exit Setup





3.14.5 GS1 DataBar Limited

Enable *



Disable




3.14.6 Transmit GS1 DataBar Limited Check

Digit

Transmit GS1 DataBar Limited

Check Digit *





Do Not Transmit GS1 DataBar Limited

Check Digit




Exit Setup





3.14.7 AI Limited

Enable *



Disable



3.14.8 Prefix/Suffix for GS1 Databar Limited

GS1 Databar Limited Prefix




GS1 Databar Limited Suffix



3.14.9 GS1 DataBar Expanded


Enable *




Disable



Exit Setup







3.14.10 Set Length Range for GS1 DataBar

Expanded

Expanded Minimum Length




Expanded Maximum Length




3.14.11 Prefix/Suffix for GS1 Databar

Expanded


GS1 Databar Expanded Prefix



GS1 Databar Expanded Suffix




Exit Setup






3.15 UPC-A

Enable *




Disable




3.15.1 Transmit UPC-A Check Digit

Transmit UPC-A Check Digit *




Do Not Transmit UPC-A Check Digit



3.15.2 UPC-A Convert to EAN-13


Enable



Disable *



Exit Setup






3.15.3 Transmit UPC-A Leading Digit

Transmit UPC-A Leading Digit *



Do Not Transmit UPC-A Leading Digit




3.15.4 Prefix/Suffix for UPC-A


UPC-A Prefix



UPC-A Suffix



Exit Setup





3.16 UPC-E

Enable *




Disable



3.16.1 Transmit UPC-E Check Digit

Transmit UPC-E Check Digit *




Do Not Transmit UPC-E Check Digit



3.16.2 Convert UPC-E to UPC-A

Enable




Disable *




Exit Setup





3.16.3 Convert UPC-E to EAN-13

Enable



Disable *



Note: If "Covert to UPC-A" and "Convert to EAN-13" are enabled both, it will convert to EAN-13.

3.16.4 Transmit Lead Zero on UPC-E

Transmit Lead Zero on UPC-E *



Do Not Transmit Lead Zero on UPC-E



3.16.5 Prefix/Suffix for UPC-E


UPC-E Prefix



UPC-E Suffix




Exit Setup





3.17 EAN/JAN-8

Enable *




Disable



3.17.1 Transmit EAN-8 Check Digit

Transmit EAN-8 Check Digit *




Do Not Transmit EAN-8 Check Digit



3.17.2 Convert EAN-8 to UPC-A


Enable




Disable *




Exit Setup





3.17.3 Convert EAN-8 to EAN-13

Enable




Disable *




3.17.4 Transmit Lead Zero on EAN-8

Transmit Lead Zero on EAN-8



Do Not Transmit Lead Zero on EAN-8 *




Note: If Convert to “UPC-A” and “Convert to EAN-13” are enabled both, it actually converts to EAN-13.

3.17.5 Prefix/Suffix for EAN-8

EAN-8 Prefix



EAN-8 Suffix




Exit Setup





3.18 EAN/JAN-13

Enable *




Disable



3.18.1 Transmit EAN-13 Leading Digit

Transmit EAN-13 Leading Digit *



Do Not Transmit EAN-13 Leading Digit



3.18.2 Transmit EAN-13 Second Digit


Transmit EAN-13 Second Digit *




Do Not Transmit EAN-13 Second Digit



Exit Setup





3.18.3 Prefix/Suffix for EAN-13

EAN-13 Prefix




EAN-13 Suffix



3.18.4 378/379 Supplemental Mode


Enable




Disable *




Exit Setup






3.18.5 978/977 Supplemental Mode

Enable



Disable *



Note: Enable [_addenda 2 digit](#) or [_addenda 5 digit](#) before enable "Supplemental Mode".

3.18.6 434/439 Supplemental Mode

Enable



Disable *



3.18.7 419/414 Supplemental Mode


Enable



Disable *



Exit Setup





3.18.8 491 Supplemental Mode

Enable




Disable *



3.18.9 978/192 Supplemental Mode


Enable




Disable *




Exit Setup





3.19 ISBN

Enable




Disable *



3.20 ISSN


Enable




Disable *



Exit Setup







3.21 Supplements +2/+5

3.21.1 Addenda 2 Digit

Enable




Disable*



3.21.2 Addenda 5 Digit

Enable



Disable*



3.21.3 Space Separator


Enable



Disable *




Exit Setup





3.22 UK/Plessey

Code UK Enable *




Code UK Disable




3.22.1 Check Digit Verification


Enable *



Disable




Transmit Check Digit After Verification




Do Not Transmit Check Digit After
Verification *




Exit Setup





3.22.2 Set Length Range for Code UK

Minimum Length



Maximum Length




3.22.3 Prefix/Suffix for Code UK


Code UK Prefix




Code UK Suffix




Exit Setup





3.23 Code ID

On




Off *




3.24 Febraban Transfer Function

On




Off *



Exit Setup





Appendix A – Digit Barcodes

A.1 ASCII Code Table (for Software Decoder Version)

SOH (start of headline)



STX (start of text)



ETX



EOT



ENQ



ACK



BEL



BS



HT



LF



VT



FF



CR



SO



SI



DLE




DC1




DC2



Exit Setup





MS836B User's Manual

DC3



DC4



NAK



SYN



ETB



CAN



EM



SUB



ESC




FS



GS



RS



US



SP



!



"



#



\$



%



&



,



(




)



*



Exit Setup





MS836B User's Manual

+



,



-



.



/



0



1



2



3



4



5



6



7



8



9



:



;



<



=



>



?



@




A




B



Exit Setup





MS836B User's Manual

C



D



E



F



G



H



I



J



K



L



M



N



O



P



Q



R



S



T



U



V



W



X




Y



Z



Exit Setup





MS836B User's Manual

[



\



]



^



-



`



^



-



`



a



b



c



d



e



f



g



h



i



j



k



l



m




n



o



Exit Setup





MS836B User's Manual

p



q



r



s



t



u



v



w



x



y



z



{



|



}



~



Insert



Del



Function Key F1



Function Key F2



Function Key F3



Function Key F4



Function Key F5



Function Key F6



Function Key F7



Exit Setup





MS836B User's Manual

Function Key F8



Function Key F9



Function Key F10



Function Key F11



Function Key F12



TAB



Back TAB



ESC



Enter



Home



PageUp



Return



PageDown



End



RightArrow



LeftArrow



DownArrow



UpArrow



Ctrl On



Ctrl Off



Alt On



Alt Off




Shift On



Shift Off



Exit Setup






Win



Exit Setup





A.2 Default Barcode Parameter Setting

Table

Types	Read	Verify Check	Transmit checking digit	Minimum length	Maximum length	ID
Industrial 2 of 5	N	N	N	4	64	A
Standard 2 of 5	N	N	N	4	64	B
MatriX 2 of 5	N	N	N	6	64	C
Chinese Postal 2 of 5	N	N	N	6	64	D
Interleave 2 of 5	YES	N	N	6	64	E
Code 11	N	YES	N	4	64	F
Codabar	YES	N	N	4	64	G
Code MSI	N	YES	N	4	64	H
Code UK	YES	YES	N	1	64	I
Code39	YES	N	N	1	64	J
Code32	N	N	N	8	8	K
Code93	YES	YES	N	1	64	L
EAN-13	YES	YES	N	13	13	O
UPC-A	YES	YES	YES	12	12	P
EAN-8	YES	YES	YES	8	8	Q
UPC-E	YES	YES	YES	7	7	R
Code128	YES	YES	N	1	100	L
RSS Truncated	YES	N	N	14	14	S
RSS Limited	YES	N	N	14	14	T
RSS Expanded	YES	N	N	1	74	M

Gray background denotes default






A.3 Default Setting Table

List	Project Name	Description	Default
1	Scan mode		Manual scan
2	Interface setting		*Automatic
3	KB/USB	Keyboard language	US
4		Function keyboard	ON
5		Enable digital keypad	Disable
6		Caplock Ignore	Not ignore
7		KB clock	10K(slow)
8	Data editing	Terminator	Enter(0x0d)
9		Caps lock	Origianl data
10		Data inversion	Disable
11		CODE ID	OFF
12		Overall Prefix and Suffix	None
13		Overall decoding length limitation	None
14		Character delay	None
15		String delay	None
16	Beeper settings	Successful decoding sound tips	Middle tone, Long duration
17		Starting sound tips	ON
18	Other functions	Repeated	None
19		Inverse barcode decoding	OFF
20		Automatic induction	ON





Appendix B – Hidden Character

B-1 Hide The Previous Character

Shortcut Settings

The format is as follows: ^&601&^ to ^&6FF&^,01~FF are hidden digits.

Do not hide the previous
characters *



Hide the first 1 bit



Hide the first 2 bits



Hide the first 3 bits



Hide the first 4 bits



Hide the first 5 bits



Hide the first 6 bits




Hide the first 7 bits




Hide the first 8 bits



Exit Setup





Hide the first 9 bits



Hide the first 10 bits



Hide the first 11 bits



Hide the first 12 bits



Hide the first 13 bits



Hide the first 14 bits



Hide the first 15 bits



Hide front Character




Hide Back Character




Saved and Finished Set



Exit Setup





B-2 Shortcut Settings to Hidden back character

The format is as follows: ^&701&^ to ^&7FF&^,01~FF are hidden digits.

Hide the last 1 bit



Hide the last 2 bits



Hide the last 3 bits



Hide the last 4 bits



Hide the last 5 bits



Hide the last 6 bits



Hide the last 7 bits



Hide the last 8 bits



Hide the last 9 bits



Hide the last 10 bits



Hide the last 11 bits




Hide the last 12 bits



Exit Setup





Hide the last 13 bits




Hide the last 14 bits



Hide the last 15 bits



Exit Setup





Appendix C – ASCII Code Table (for RFID Module)

Null



SOH(start of headline)



STX (start of text)



ETX



EOT



ENQ



ACK



BEL



BS



HT



LF



VT



FF



CR



SO



SI



DLE



DC1



DC2



DC3



DC4



NAK



SYN




ETB




CAN



Exit Setup





MS836B User's Manual

EM



SUB



ESC



FS



GS



RS



US



SP



!



"



#



\$



%



&



.



(



)



*



+



,



-



.



/



0



1



2



3



4



5



6



7




8




9



Exit Setup






MS836B User's Manual



Exit Setup





MS836B User's Manual



Exit Setup





MS836B User's Manual



DEL



Caps Lock



Function Key F1



Function Key F2



Function Key F3



Function Key F4



Function Key F5



Function Key F6



Function Key F7



Function Key F8



Function Key F9



Function Key F10



Function Key F11



Function Key F12



PrintScreen



Scroll Lock



Pause



Insert



Home



PageUp



Delete



PageDown



End



RightArrow



LeftArrow



DownArrow



UpArrow



Num Lock(keypad)




/(keypad)



*(keypad)

Exit Setup





MS836B User's Manual

-(keypad)



+(keypad)



Enter(keypad)



1(keypad)



2(keypad)



3(keypad)



4(keypad)



5(keypad)



6(keypad)



7(keypad)



8(keypad)



9(keypad)



0(keypad)



.(keypad)




Exit Setup







Dec	Hex	Char
0	00	NUL (Null char.)
1	01	SOH (Start of Header)
2	02	STX (Start of Text)
3	03	ETX (End of Text)
4	04	EOT (End of Transmission)
5	05	ENQ (Enquiry)
6	06	ACK (Acknowledgment)
7	07	BEL (Bell)
8	08	BS (Backspace)
9	09	HT (Horizontal Tab)
10	0A	LF (Line Feed)
11	0B	VT (Vertical Tab)
12	0C	FF (Form Feed)
13	0D	CR (Carriage Return)
14	0E	SO (Shift Out)
15	0F	SI (Shift In)
16	10	DLE (Data Link Escape)
17	11	DC1 (XON) (Device Control 1)
18	12	DC2 (Device Control 2)
19	13	DC3 (XOFF) (Device Control 3)
20	14	DC4 (Device Control 4)
21	15	NAK (Negative Acknowledgment)
22	16	SYN (Synchronous Idle)
23	17	ETB (End of Trans. Block)
24	18	CAN (Cancel)
25	19	EM (End of Medium)
26	1A	SUB (Substitute)
27	1B	ESC (Escape)
28	1C	FS (File Separator)
29	1D	GS (Group Separator)
30	1E	RS (Request to Send)
31	1F	US (Unit Separator)

Exit Setup






Dec	Hex	Char
32	20	<SPACE>
33	21	!
34	22	"
35	23	#
36	24	\$
37	25	%
38	26	&
39	27	'
40	28	(
41	29	)
42	2A	*
43	2B	+
44	2C	,
45	2D	-
46	2E	.
47	2F	/
48	30	0
49	31	1
50	32	2
51	33	3
52	34	4
53	35	5
54	36	6
55	37	7
56	38	8
57	39	9
58	3A	:
59	3B	;
60	3C	<
61	3D	=






Dec	Hex	Char
62	3E	>
63	3F	?
64	40	@
65	41	A
66	42	B
67	43	C
68	44	D
69	45	E
70	46	F
71	47	G
72	48	H
73	49	I
74	4A	J
75	4B	K
76	4C	L
77	4D	M
78	4E	N
79	4F	O
80	50	P
81	51	Q
82	52	R
83	53	S
84	54	T
85	55	U
86	56	V
87	57	W
88	58	X
89	59	Y
90	5A	Z
91	5B	[
92	5C	\
93	5D	]
94	5E	^

Exit Setup





Dec	Hex	Char
95	5F	—
96	60	`
97	61	a
98	62	b
99	63	c
100	64	d
101	65	e
102	66	f
103	67	g
104	68	h
105	69	i
106	6A	j
107	6B	k
108	6C	l
109	6D	m
110	6E	n
111	6F	o
112	70	p
113	71	q
114	72	r
115	73	s
116	74	s
117	75	u
118	76	v
119	77	w
120	78	x
121	79	y
122	7A	z
123	7B	{
124	7C	
125	7D	}
126	7E	~
127	7F	DEL







Appendix D – Function Code for Serial Port and USB Virtual Serial Port


Hex	Dec	Char
00	0	NUL (Null char.)
01	1	SOH (Start of Header)
02	2	STX (Start of Text)
03	3	ETX (End of Text)
04	4	EOT (End of Transmission)
05	5	ENQ (Enquiry)
06	6	ACK (Acknowledgment)
07	7	BEL (Bell)
08	8	BS (Backspace)
09	9	HT (Horizontal Tab)
0A	10	LF (Line Feed)
0B	11	VT (Vertical Tab)
0C	12	FF (Form Feed)
0D	13	CR (Carriage Return)
0E	14	SO (Shift Out)
0F	15	SI (Shift In)
10	16	DLE (Data Link Escape)
11	17	DC1 (XON) (Device Control 1)
12	18	DC2 (Device Control 2)
13	19	DC3 (XOFF) (Device Control 3)
14	20	DC4 (Device Control 4)
15	21	NAK (Negative Acknowledgment)
16	22	SYN (Synchronous Idle)
17	23	ETB (End of Trans. Block)
18	24	CAN (Cancel)
19	25	EM (End of Medium)

Exit Setup





Hex	Dec	Char
1A	26	SUB (Substitute)
1B	27	ESC (Escape)
1C	28	FS (File Separator)
1D	29	GS (Group Separator)
1E	30	RS (Request to Send)
1F	31	US (Unit Separator)





Appendix E – The Default Value Of Each Symbology's Length Within Range

Symbology	Default Minimum Length	Default Maximum Length
Industrial 2 of 5	4	64
Standard 2 of 5	4	64
Matrix 2 of 5	4	64
Chinese Postal 2 of 5	4	64
Interleaved 2 of 5	4	64
Code 11	4	64
Codabar	4	64
Code MSI	4	64
Code UK	1	64
Code 39	1	64
Code 32	8	8
Code 93	1	64
EAN-13	13	13
UPC-A	12	12
EAN-8	8	8
UPC-E	7	7
Code 128	1	100
GS1 Databar Truncated	14	14
GS1 Databar Limited	14	14
GS1 Databar Expanded	1	74

